

# HITACHI

## Inspire the Next

## Quick installation guide

# Hitachi Deskstar T7K250

### Ultra ATA/133 Hard disk drive



#### Models:

HDS722525DLAT80  
HDS722516DLAT80

---

#### System requirements for Ultra ATA/133

---

If you do not have the components listed below, your drive will function but at speeds lower than 133 MB/s.

- 40-pin, 80-conductor cable
- A controller card or motherboard chipset with Ultra ATA/133 capability
- Ultra ATA/133 compatible BIOS or driver

---

#### Handling precautions

---

- Set the drive down gently to prevent damage from impact or vibration.
- Do not open the ESD bag containing the drive until needed.
- Handle the drive carefully by the edges. Do not touch the exposed printed circuit board or any electronic components.
- Do not press on the top or bottom of the drive.
- Do not cover the drive breather hole.
- Before handling the drive, discharge any static electricity from yourself and your clothing. With one hand touch an unpainted metal surface on your computer chassis, then touch the ESD bag with the other hand. Remain in contact with the chassis and the bag for a minimum of two seconds.


---

#### Quick installation procedure

---

Note: Back up all data before installing drive!

1. Turn off the computer.
2. Unplug the computer
3. Remove the computer cover as instructed by the computer system manual.
4. Discharge static electricity (see Handling precautions).
5. Note the mounting position of existing drives and cables. If you are replacing a drive or any cable, remove it now.
6. Remove the drive from the ESD bag.
7. Record the model, the part number, and the serial number of the drive for future reference.
8. Insert the required jumpers. Refer to the jumper block diagram below.
  - If the drive is the only drive on a cable or the master drive on a two-drive cable, leave the jumpers as set at A-B and G-H for 16 head logical architecture. The jumpers are factory-set to Master-16 heads.
  - If the drive is the slave drive on a two-drive cable, set the jumpers at A-B and C-D for 16-head logical architecture.



9. Attach the IDE cable.
  - If you have a 40-pin 40-conductor cable, attach the system connector of the cable to the IDE port on the motherboard or controller card. The pin 1 side of the IDE cable is marked with a stripe. The connector can only be inserted one way.
  - If you have a 40-pin 80-conductor cable, attach the drive to the appropriate color-coded connector. Forty-pin 80-conductor cables are color-coded black for Master, gray for Slave, and blue for system connectors.
10. Attach the power supply cable to the drive. Match the connector bevels.
11. Mount the drive securely.
12. Verify all attachments.
13. Replace the computer cover.
14. Plug in the computer.
15. Turn on the computer.
16. Verify that the hard disk is recognized by the BIOS and is reporting the full capacity of the drive. Instructions for accessing your BIOS can be found in the computer system manual or in the motherboard manufacturer documentation. If the drive is not recognized in the BIOS, set the BIOS options of your computer system to Auto Detection and LBA mode if available. Once the drive is recognized correctly in the BIOS, it is ready to be partitioned and formatted.

#### **137GB Limitation**

With the 160GB and 250GB model, you may encounter a BIOS limitation of 137GB. Possible solutions for the 137GB limitation include operating system patches, 3<sup>rd</sup> party hardware or BIOS upgrade. If you would like additional information about the 137GB limitation and possible 3<sup>rd</sup> party solutions, see the FAQ "What is the 137GB limitation" at: [www.hitachigst.com/support](http://www.hitachigst.com/support)

17. Your operating system setup utility will provide instructions on how to partition and format your drive before it installs the operating system. For additional information see:

[www.hitachigst.com/support](http://www.hitachigst.com/support)

---

© Copyright Hitachi Global Storage Technologies

Hitachi Global Storage Technologies  
5600 Cottle Road  
San Jose, CA 95193

Produced in the United States

1/05

All rights reserved Deskstar™ is a trademark of Hitachi Global Storage Technologies.

Microsoft, Windows XP, and Windows are trademarks of Microsoft Corporation in the United States, other countries, or both.

Other product names are trademarks or registered trademarks of their respective companies.

References in this publication to Hitachi Global Storage Technologies products, programs or services do not imply that Hitachi Global Storage Technologies intends to make these available in all countries in which Hitachi Global Storage Technologies operates.

Product information is provided for information purposes only and does not constitute a warranty.

Information is true as of the date of publication and is subject to change. Actual results may vary.

This publication is for general guidance only. Photographs may show design models.

12 January 2005

---